

8500

DC BATTERY BACKUP CAPABLE WALL MOUNT GARAGE DOOR OPENER



Wall Mount Design: The Simple Beauty of an Open Space



Connectivity

- **MyQ® Technology** enables you to securely monitor and control your garage door opener and houselights with your smartphone, tablet or computer. (Requires purchase of Internet Gateway (828LM)).
- **Alerts** can be received as email or pop-up (push) notifications on your mobile device so that you always know the status of your garage door and houselights.
- **MyQ mobile app** is a free download requiring no activation or subscription fees.

Performance

- **P3™ Motors** are reliable, durable and powerful – designed specifically for your needs.
- **Ultra-quiet** eliminates sound and vibration through the ceiling – perfect if you have a home with a room above or next to the garage.
- **Battery Backup** powers up even when power is out so you can get in your garage (Requires purchase of 475LM Battery Backup).
- **Wall mount design** frees the garage ceiling of hanging operators and rails and opens up the space for additional storage – ideal for cathedral or obstructed ceilings.
- **Remote light** delivers 200 watts of light with adjustable light time delay.
- **Lifetime motor** and 5-year parts warranty. 1-year Battery Backup warranty (Sold separately).

Safety and Security

- **Security+ 2.0®** safeguards your household – with every click a new code is sent to the garage door opener so that the door opens only for you.
- **Timer-to-Close** remembers to close your garage door when you forget – automatically closes the door after a pre-programmed number of minutes.
- **Alert-2-Close** warning system provides audible and visual warnings when the garage door is about to close when using MyQ Technology or Timer-to-Close.
- **Motion detector** activates the garage door opener lights as soon as you walk in so no more fumbling in the dark.
- **The Protector System®** has safety sensors that project a light beam across the garage door opening automatically reversing the door if anything interrupts the beam.
- **Power Lock Deadbolt (041A6102)** ensures the door cannot be forced open.

Included Accessories:



3-Button Elite Remote Control (895MAX)

Allows you to control up to three garage door openers, gate operators or MyQ Light Accessories. Sleek contoured design with bright blue LED lights.



MyQ Control Panel (888LM)

Allows any garage door opener manufactured since 1998 to be controlled by your smartphone, tablet or computer (when paired with the Internet Gateway) – provides the upgrade needed to utilize Security+ 2.0 and MyQ Technology.



Remote Light (380LM)

Light your space the way you want to by placing this anywhere in the garage. Uses (2) 100 watt bulbs (not included).

Optional Accessories:



Internet Gateway (828LM)

Connect your MyQ-Enabled Garage Door Opener and Accessories to the Internet with this device and the free MyQ app.



Remote Light Control (825LM)

Allows you to control any lamp with your garage door opener remote control or smartphone via the Internet Gateway and the free MyQ app.



Door and Gate Monitor (829LM)

Enables you to monitor and close up to four garage doors or gates from any room in your house.



Battery Backup (475LM)

Powers up even when power is out so you can get in your garage.

SPEC SHEET STANDARD SPECIFICATIONS

DIMENSIONS

Garage Door Opener Dimensions:
- 6.85"D x 16.25"H x 6.01"W
Maximum Door Size:
- Up to 14' High, total of 180 Square Feet
Headroom Clearance Required:
- 3" from center of Torsion Bar

CARTONS

Number of Cartons: 1
Carton Dimensions and Contents:
- 24" x 10" x 12"
- MyQ® Control Panel
- 895MAX Premium Remote Control
- Garage Door Opener Head
- Power Door Lock
- Cable Tension Monitor
- Remote Light
- The Protector System® Safety Reversing Sensors

SECURITY+ 2.0® RADIO CONTROLS

895MAX Premium Remote Control
Operating Range: 200' (approximately)
Operating Temperature: -40°F to 150°F
Frequency:
- Remote Control: 315 MHZ / 390 MHZ Dual Band*
- Receiver: Frequency Agile on 310, 315 & 390 MHZ
Security+ 2.0 Anti-Burglary Coding
*Dual Band on Security+2.0 coding only. Premium Remote Control is backwards compatible to all LiftMaster openers manufactured since January 1993.

MYQ RADIO

902-928 MHz
50 Channel FHSS (Frequency Hopping Spread Spectrum)
Provides two-way communication from garage door opener and MyQ Accessories.*
Enables Remote Closing of garage door with key MyQ Accessories.
Enables monitoring and control of garage door openers and lighting controls via computer, tablet, or smartphone.**
*MyQ radio disabled in battery backup mode or when using Alternate Power System (580LM)
**Requires Internet Gateway Accessory Model 828LM

WALL CONTROL

888LM MyQ Control Panel
- MyQ and Security+ 2.0 Radio*
- Timer-to-Close
- Motion Detecting: Hands free opener lights on
- Light Control: Turns opener lights on/off
- Lock Mode: Locks out remote controls
- Program remote controls, keypads and MyQ Accessories
*Because the radios reside in the control panel, alternate wired control panels should not be used with this operator.

SECURITY+ 2.0 ENCRYPTED CONTROLS

888LM MyQ Control Panel
- Timer-to-Close
- Program Remote Controls, Keypads and MyQ Accessories
- Maintenance Alert System

CONVENIENCE / SAFETY

The Protector System Safety Reversing Sensors
Battery Backup Capable compatible model 475LM (optional accessory)
Alert-2-Close Unattended Close Operation w/ Select Accessories*
Hands Free Work Lights On
Emergency / Quick Release
Ventilation / Pet Opening
Down Safety Reverse
Up Safety Stop
Door Open/Beam Obstructed / Lights On
Slow Start Soft Stop
*Unattended Operation functionality cannot be utilized when opener is installed on a one-piece door.

ELECTRICAL SPECIFICATIONS

POWER

Voltage: 120V AC, 60Hz
Current Rating: 2.7A
UL Listings: Yes
Length of Line Cord: 6' (1829 mm), 3-prong
Worklight Voltage: 120V AC, 60Hz

ENERGY EFFICIENCY

Approximately 1 Watt Power in Standby Mode*
Enhanced CFL (Compact Fluorescent) Compatible
*Standby Mode at down limit, work lights off

LOGIC TYPE

Solid-State Microcontroller with Built-in Surge Suppressor

LIGHTING

Remote light control fixture can be located anywhere in garage
Number of Bulbs: 2
Maximum Wattage: 100 x 2
Adjustable Time, Solid-State Delay
(1.5 to 4.5 minutes)

MECHANICAL SPECIFICATIONS

MOTOR

Heavy-Duty 24V DC Motor
Rotational Torque: 255 in·lbf
Thermal Protection: Automatic
Lubrication: Permanent

DRIVE MECHANISM

Drive Means: Internal Chain and Sprocket
Reduction Means: Gear 63:1

ADJUSTMENTS

Auto Force
Electronic Limit Settings

TRAVEL RATE

Approximately 7.6" per second

SHIPPING WEIGHTS

Entire System: 31 lbs.

MATERIALS

Chassis: Steel
Cover: Plastic

INSTALLATION AIDS (OPTIONAL)

Obstructions:
- Alternate Mounting Kit (480LM)*
- Lowers opener by 6"
Power Outlet Availability:
- Alternate Power System (580LM)*
- For use when outlet not within 6'
- Electrician not required
- 24V Transformer
- 35' low voltage cable
- Interface to Battery Backup System (475LM)
*MyQ radio disabled when in battery backup mode or when using Alternate Power System (580LM).

WARRANTY

Lifetime Motor Warranty
5 Years Parts Warranty
1 Year Accessories Warranty
1 Year Battery Backup System (475LM)
(sold separately)

HOMELINK® Compatible (version 4.0 or higher)*

*May require an external adapter depending on the model and year of your vehicle.
Visit homelink.com for additional information.



12718 E Indiana Ave
Spokane, WA 99216

(509) 921-2260 • (509) 921-5099 Fax

www.continentaldoorco.com

Note: To reduce the risk of injury to persons, when the Internet Gateway is used with garage door openers, the operator must be installed with sectional doors.